



## DIN-FB Din Rail Terminal Box

DIN-FB Series plastic terminal box is suitable for protective connection of fiber optic cable and pigtail, the box is made of ABS + PC flame retardant plastic, and the adapter panel is made of high quality cold plate material. This terminal box is mounted on the din rail.

### Applications

- Internal application
- Data Centre or telecommunications networks
- For use in multi dwelling units or demarcation points within a network

### Features

- ABS + PC flame retardant plastic material, light, meet the UL94-V0
- Flip design, compact structure and easy operation
- Variety of iron adapter strips, customised
- DIN rail mounting, without screwing, easy maintenance
- Bracket supporting, can be installed in the cabinet

## Specifications

ELEMENT	VALUE	
Height	133mm	
Width	35mm	
Depth	130mm	
Suitable for Adaptor Type	SC Simplex, SC Duplex, LC, ST, FC	
Number of fibres	12	
Material	ABS + PC flame retardant plastic	
Operating Temperature	-40°C to +60°C	
Compliant to	RoHS, Reach/SVHC	
Packaging	Dimension	Weight
Pizza Box	16.5*15.5*4.5cm	0.5Kgs
Carton	48.5*47*35cm	24Kgs

## Ordering Information

DIN-FB																																																
DIN-FB Series Plastic Terminal Box																																																
<table border="1"> <thead> <tr> <th colspan="2">Adaptor</th> </tr> </thead> <tbody> <tr><td>00</td><td>LC</td></tr> <tr><td>01</td><td>LCA</td></tr> <tr><td>02</td><td>SC</td></tr> <tr><td>03</td><td>SCA</td></tr> <tr><td>04</td><td>ST</td></tr> <tr><td>05</td><td>FC</td></tr> <tr><td>06</td><td>FCA</td></tr> </tbody> </table>	Adaptor		00	LC	01	LCA	02	SC	03	SCA	04	ST	05	FC	06	FCA	+	<table border="1"> <thead> <tr> <th colspan="2">Fibre Type</th> </tr> </thead> <tbody> <tr><td>9</td><td>Singlemode</td></tr> <tr><td>2</td><td>Multimode (OM1/OM2)</td></tr> <tr><td>3</td><td>OM3</td></tr> <tr><td>4</td><td>OM4</td></tr> </tbody> </table>	Fibre Type		9	Singlemode	2	Multimode (OM1/OM2)	3	OM3	4	OM4	+	<table border="1"> <thead> <tr> <th colspan="2">Configuration</th> </tr> </thead> <tbody> <tr><td>1</td><td>Simplex</td></tr> <tr><td>2</td><td>Duplex (Only for LC)</td></tr> </tbody> </table>	Configuration		1	Simplex	2	Duplex (Only for LC)	+	<table border="1"> <thead> <tr> <th colspan="2">Adaptor Count</th> </tr> </thead> <tbody> <tr><td>02</td><td>2</td></tr> <tr><td>04</td><td>4</td></tr> <tr><td>...</td><td>...</td></tr> <tr><td>12</td><td>12</td></tr> </tbody> </table>	Adaptor Count		02	2	04	4	...	...	12	12
Adaptor																																																
00	LC																																															
01	LCA																																															
02	SC																																															
03	SCA																																															
04	ST																																															
05	FC																																															
06	FCA																																															
Fibre Type																																																
9	Singlemode																																															
2	Multimode (OM1/OM2)																																															
3	OM3																																															
4	OM4																																															
Configuration																																																
1	Simplex																																															
2	Duplex (Only for LC)																																															
Adaptor Count																																																
02	2																																															
04	4																																															
...	...																																															
12	12																																															

### Example:

**DIN-FB-02-91-12** – Din Rail Fibre Terminal Box loaded with 12 SC Simplex Singlemode Adaptors

Additional Images

